



PA Amplifier AP-DM30TM, AP-DM60TM 30W/60W Desktop Amplifier with Digital



AP-DM30TM, AP-DM60TM 30W/60W Desktop Amplifier with Digital Player

Features :

- 30W & 60W RMS rated power mixer output
- Built-in MP3 player by USB, FM tuner and Bluetooth
- 3 Microphone & 2 line inputs, 1 Line output
- Supports multiple speaker outputs 100V, 70V and 4 ~ 16 Ohms
- Emergency input with highest priority announcement
- Automatic mute function for paging and announcements
- Front panel with controls buttons, Priority MIC inputs, LED indicators
- Individual Volume Controls for MIC/Aux, Bass & treble, and Digital tuner
- Safety measures precaution for short circuit, overload & high temp.
- Standard power 220-240V AC input (Optional 110V and DC operation)
- Ideally for Basic small PA, Standard PA, BGM system and Mixer amplifier application

APPLICATIONS

Auditorium & Outdoor Events



Disco Clubs & Restaurant



Apartment & Corporates



Technical Specifications

Model No.	AP-DM30TM	AP-DM60TM
Rated power output	30W RMS	60W RMS
Inputs	3 x MIC In, 2 x Line in	
Outputs	1 x Line out	
Emergency input	MIC 1 with Priority Input at on front panel	
Controls	MIC volume, Treble, Bass, Master, Power switch	
Tone controls	Bass 100Hz(+/- 10dB), Treble 12KHz(+/- 10dB)	
Speaker Out	100V, 70V, 4 ~ 16Ω	
Frequency response	60Hz ~ 15KHz, +/- 3dB	
S/N ratio	>73dB	
THD	<0.5% at 1KHz	
Protection	High temperature, Short Circuit, Overload	
Power input	220-260V AC	
Power consumption	60W	100W
Working temp. & Humidity	0°C ~ 40°C, ≤ 95%RH (Not condensing)	
Mount	Table top, 2U	
Enclosure & Color	Steel, Black	
Dimension & Weight	"88(H) x 300(W)x 270(D), <3.5Kg"	<7Kg

