



## Analog PA AP-Z218 16 Zone Speaker Selector



# AP-Z218 16 Zone Speaker Selector

### Features :

- 16 Zone speaker out and 4CH audio inputs
- 4 x 4 matrix with priority override
- 16 speaker zones are divided into 4 groups
- Priority Input and Alarm Output Ports, Priority access for all 16 Zone
- Each group can have a separate audio source
- Zone selector works with AP-Z215 Zone paging selector and AP-Z214 Paging station and expandable up to 120 Zones
- Direct input from AP-Z221 to EMC1 can generate emergency announcement & Alarm siren for connected devices
- Hi-Power handling capacity up to 1.5KW
- 19" Ready rack mount installation design

### APPLICATIONS

Shopping Mall



Hotel & Restaurant



Warehouse



## Technical Specifications

Model No.	AP-Z218
Input	4 programm and 1 Priority Channel, 100V/70V Audio Signal
Zone Speaker Out	16 Zone, Divided in 4 groups X 4 Zone each
Power Handling	375W/per channel, Total Capacity 1.5KW
Priority Contact Input	16 Zone, Activated by 0V Trigger Signal
Alarm Output	0V Trigger Signal
Control	16 Zone Push button, 1 Power Switch
Power Input	200-240V AC, Fuse Protection
Power Consumption	<20W
Mount	2U 19" Rack Mount, Table Top
Enclosure & Color	Full Metal, Black
Dimension & Weight	89(H) x 483(W) x 366(D) mm, <8Kg

