



## PA Amplifier AS-MCA516 500W Mixer Amplifier



## AS-MCA516 500W Mixer Amplifier

The Public Address (PA) 500 Watts Mixer Amplifier is suitable for school, super market, bank, hotel BGM and speech use.

It integrates pre amplifier and mixer power amplifier into one 19" 3U height unit of tabletop design, which is economy but of high reliable performance.

The tabletop mixer amplifier rated power out at 500W. Its speaker outputs with 100V, 70V and 4-16ohms for versatile connections.

The amplifier is designed with complete protection of overload, short circuit and high temp to avoid any damage.

### Features :

- Public address (PA) tabletop mixer power amplifier.
- Commercial & industrial range BGM & paging amplifier.
- Rated outputs of 500W.
- 70V, 100V and low impedance 2-4 ohms speaker outputs.
- 6 microphone inputs and 2 line inputs.
- Microphone 1-4 & Aux/Mic 5-6 inputs volume control on front panel with bass and treble tone control.
- Line inputs/outputs on rear panel.
- Overload, short circuit and high temp protection.
- Power, Volume, Output Bar Graph LED.
- Overload, short circuit and high temp protection

## Technical Specifications

<b>Model No.</b>	<b>AS-MCA516</b>
Description	Public Address System 500W Mixer Amplifier
Rated Power Output	500W RMS
Speaker Output	70V, 100V and 4-16Ω
Input	Mic1-4: 600 ohms(Ω) 5-8 mV, unbalanced, Aux1-2: 10k ohms(Ω) 150-470 mV, unbalanced
Frequency Response	60-15KHz
THD	<0.5% at 1kHz, 1/3 rated power
S/N Ratio	Line: 85 dB , MIC: >72 dB
Controls	2 Way Tone Control, Horn / Speaker Switch, Sliding Master Control
Power Supply	AC230V or AC110V, 50-60Hz
Power Consumption	600W
Protection	High temp, short circuit, overload protection
Dimension	485(W)×430(D)×155(H)mm
Net. Weight	<19.0kg
Gross Weight	<21.kg
Warranty	1 years

## APPLICATIONS

**Auditorium & Outdoor Events**



**Disco Clubs & Restaurant**



**Apartment & Corporates**

