

## AP-D408 16 Zone Digital Remote Paging Station

## **Features :**

- AP-D408 Remote Paging Microphone works together with the AP-D407 Paging Selector
- Manages up to 8pcs of AP-D407, Total of 128 loudspeaker lines
- Communication distance max. 600meters
- Built-in Chime tone
- On/Off Power Button

## **APPLICATIONS**









## **Technical Specifications**

Model No.	AP-D408
Mic Input	600ohms,5mv un balanced
Line Output	10K Ohms, 10v balanced
Frequency Response	MIC. Line: 60Hz -16kHz (+/- 3dB)
S/N Ratio	Better than 70dB
THD	Less than 0.1%at1kHz
Zone Controls	16 zones, Zone 1 to Zone 16, up to 128 zones w/ address selector
Indicators	Indicators for 16 zones and 8 speaker selectors, MIC on/off
Power Input	24V DC, Fuse Protection
Power Consumption	<8W
Mount	2U 19" Rack Mount, Table Top
Enclosure & Color	Full Metal, Black
Dimension & Weight	70(H) x 238(W) x 170(D) mm, <3.5Kg



A Venture of **ADIT GROUP** 



\*Product specifications and appearance may be changed without prior notice due to improvements

Follow us : (i) 🗿 🚯 🎯 🏈

AUDIO | VIDEO | THERMAL | UTP