

# AP-Z219 2 x 5 Zone Speaker Selector

#### Features :

- 10 Zone speaker out and 2CH Audio input
- 2 port Hi-Power amplifier inputs
- Speaker selector divided into 5 Zone selectors with separate audio sources or Single 10 zone selector with a single audio Input
- Each group can have a separate audio source
- Zone selector works with AP-Z215 Zone paging selector and AP-Z214 Paging station and expandable up to 120 Zones
- High Power Handling Capacity up to 1.5KW
- 19" Ready rack mount installation design

#### **APPLICATIONS**









Technical Specifications	
Model No.	AP-Z219
Input	2 program, 100V/70V Audio Signal
Zone Speaker Out	10 Zone, Divided in 2 groups X 5 Zone each
Power Handling	150W/per channel, Total Capacity 1.5KW
Priority Contact Input	N.A
Alarm Output	N.A
Control	16 Zone Push button, 1 Power Switch
Power Input	200-240V AC, Fuse Protection
Power Consumption	<20W
Mount	2U 19" Rack Mount, Table Top
Enclosure & Color	Full Metal, Black
Dimension & Weight	89(H) x 483(W) x 366(D) mm, <8Kg

### 



A Venture of **ADIT GROUP** 



Scan with your Smart phone for more information avtrontech.com info@avtrontech.com

\*Product specifictions and appearance may be changed without prior notice due to improvements

Follow us : 💿 🖸 🚺 🕥 🏈

## AUDIO | VIDEO | THERMAL | UTP